

HV610 Serisi İverter Frenleme Direnci			
Voltaj(V)	İverter Kw	Watt	Ohm
3x380V G3 Serisi	0,75	300	800
	1,5	600	400
	2,20	880	250
	4,0	1100	150
	5,50	2200	100
	7,5	3000	75
	11,00	4500	50
	15,0	6000	40
	18,50	4000	60
	22,0	4500	60
	30,00	6000	40
	37,0	5000	42
	45,00	6000	30
	55,0	5000	40
	75,00	5000	39
	93,0	5000	40
	110,00	5000	40
	132,0	6000	33
	160,00	5000	39
	185,0	5000	39
	200,00	5000	40
	220,0	5000	40
	250,00	5000	38
	280,0	5000	41
	315,00	5000	39
	355,0	5000	42
	400,00	5000	38
	450,0	5000	36
	500,00	5000	36
	560,0	5000	36